

IM41DP01-E2

Thank you for purchasing the RKC instrument. In order to achieve maximum performance and ensure proper operation of your new instrument, carefully read all the instructions in this manual. Please place this manual in a convenient location for easy reference.

SYMBOLS

WARNING :


This mark indicates precautions that must be taken if there is danger of electric shock, fire, etc., which could result in loss of life or injury.

CAUTION :

This mark indicates that if these precautions and operating procedures are not taken, damage to the instrument may result.

NOTE :

Extra notes or precautions are added to operating procedures and explanations.

 : This mark indicates that all precautions should be taken for safe usage.

* : This mark is used to add extra notes, precautions or supplementary explanations to table and figures.

- This is a Class A instrument. In a domestic environment, this instrument may cause radio interference, in which case the user may be required to take adequate measures.
- This instrument is protected from electric shock by reinforced insulation. Provide reinforced insulation between the wire for the input signal and the wires for instrument power supply, source of power and loads.
- This instrument is designed for installation in an enclosed instrumentation panel. All high-voltage connections such as power supply terminals must be enclosed in the instrumentation panel to avoid electric shock by operating personnel.
- All precautions described in this manual should be taken to avoid damage to the instrument or equipment.
- All wiring must be in accordance with local codes and regulations.
- To prevent instrument damage or failure, protect the power line and the input/output lines from high currents with a protection device such as fuse, circuit breaker, etc.
- Prevent metal fragments or lead wire scraps from falling inside instrument case to avoid electric shock, fire or malfunction.
- Tighten each terminal screw to the specified torque found in the manual to avoid electric shock, fire or malfunction.
- For proper operation of this instrument, provide adequate ventilation for heat dispensation.
- Do not connect wires to unused terminals as this will interfere with proper operation of the instrument.
- Turn off the power supply before cleaning the instrument.
- Do not use a volatile solvent such as paint thinner to clean the instrument. Deformation or discoloration will occur. Use a soft, dry cloth to remove stains from the instrument.
- To avoid damage to instrument display, do not rub with an abrasive material or push front panel with a hard object.

 **WARNING**

- An external protection device must be installed if failure of this instrument could result in damage to the instrument, equipment or injury to personnel.
- All wiring must be completed before power is turned on to prevent electric shock, fire or damage to instrument and equipment.
- This instrument must be used in accordance with the specifications to prevent fire or damage to instrument and equipment.
- This instrument is not intended for use in locations subject to flammable or explosive gases.
- Do not touch high-voltage connections such as power supply terminals, etc. to avoid electric shock.
- RKC is not responsible if this instrument is repaired, modified or disassembled by other than factory-approved personnel. Malfunction can occur and warranty is void under these conditions.

NOTICE

- This manual assumes that the reader has a fundamental knowledge of the principles of electricity, process control, computer technology and communications.
- The figures, diagrams and numeric values used in this manual are only for purpose of illustration.
- RKC is not responsible for any damage or injury that is caused as a result of using this instrument, instrument failure or indirect damage.
- Periodic maintenance is required for safe and proper operation of this instrument. Some components have a limited service life, or characteristics that change over time.
- Every effort has been made to ensure accuracy of all information contained herein. RKC makes no warranty expressed or implied, with respect to the accuracy of the information. The information in this manual is subject to change without prior notice.
- No portion of this document may be reprinted, modified, copied, transmitted, digitized, stored, processed or retrieved through any mechanical, electronic, optical or other means without prior written approval from RKC.

1. PRODUCT CHECK

Check whether the delivered product is as specified by referring to the following model code list.

Model code

REX-DP110 -
 ① ② ③

REX-DP410 -
 ① ② ③

- ① Input type...See 6. INPUT RANGE TABLE.
- ② Input range...See 6. INPUT RANGE TABLE.
- ③ Power supply type
 3: 24 V AC/DC 4: 100 to 240 V AC

Accessories

- Mounting brackets (2 pieces)
- Instruction Manual [IM41DP01-E2] (1 copy)

2. MOUNTING





To prevent electric shock or instrument failure, always turn off the power before mounting or removing the instrument.

■ Cautions for mounting

- (1) This instrument is intended to be used under the following environmental conditions. (IEC61010-1)
 [OVERVOLTAGE CATEGORY II, POLLUTION DEGREE 2]
- (2) Avoid the following when selecting the mounting location.

- Ambient temperature of less than 0°C or more than 50°C .
- Ambient humidity of less than 45 % or more than 85 % RH.
- Rapid changes in ambient temperature which may cause condensation.
- Corrosive or inflammable gases.
- Direct vibration or shock to the mainframe.
- Water, oil, chemicals, vapor or steam splashes.
- Excessive dust, salt or iron particles.
- Excessive induction noise, static electricity, magnetic fields or noise.
- Direct air flow from an air conditioner.
- Exposure to direct sunlight.
- Excessive heat accumulation.

■ Dimensions



■ Mounting procedures


● REX-DP110

<When the instruments are mounted on panel with 1 to 5 mm in thickness>

Since the mounting brackets are already installed on the instrument, insert the instrument into the panel front without removal of the brackets.


<When the instruments are mounted on panel with 5 to 9 mm in thickness>

Remove the mounting brackets from the instrument with a slotted screwdriver. Engage each mounting bracket with holes marked with "5-9" on the housing and then insert the instrument through from the panel cutout.



● REX-DP410

- ① Prepare the panel cutout as specified in Dimensions.
- ② Insert the instrument through the panel cutout.
- ③ Insert an upper mounting bracket along the bracket insertion groove from the back, and then engage a projection at the bracket end with a recess at the groove front and also insert metal fitting legs into slots.
- ④ Tighten a bracket setscrew from the rear of the bracket with Phillips screwdriver. Do not overtighten the bracket setscrew.
- ⑤ The other mounting bracket should be installed in the same way described in ③ and ④.




3. WIRING

⚠ WARNING

To prevent electric shock or instrument failure, do not turn on the power until all the wiring is completed.


■ Cautions for wiring

- (1) For thermocouple input, use the specified compensation wire.
- (2) For RTD input, use low resistance lead wire with no difference in resistance between the three lead wires.
- (3) To avoid noise induction, keep input signal wire away from instrument power line, load lines and power lines of other electric equipment.
- (4) If there is electrical noise in the vicinity of the instrument that could affect operation, use a noise filter.
 - Shorten the distance between the twisted power supply wire pitches to achieve the most effective noise reduction.
 - Always install the noise filter on a grounded panel. Minimize the wiring distance between the noise filter output and the instrument power supply terminals to achieve the most effective noise reduction.
 - Do not connect fuses or switches to the noise filter output wiring as this will reduce the effectiveness of the noise filter.
- (5) Power supply wiring must be twisted and have a low voltage drop.
- (6) About five or six seconds are required as preparation time for contact output every time the instrument is turned on. Use a delay relay when the output line is used for an external interlock circuit.
- (7) This instrument is not furnished with a power supply switch or fuse. Therefore, if a fuse or power supply switch is required, install close to the instrument. [Recommended fuse rating: Rated voltage 250 V, Rated current 1 A Fuse type: Time-lag fuse]
- (8) For the current input specification, a resistor of $250\Omega \pm 0.02\% \pm 10 \text{ ppm}$, 0.25 W or more) must be connected between the input terminals. This resistor must be provided by the customer.
- (9) Do not excessively tighten the terminal screws. In addition, use the solderless terminal appropriate to the screw size. (Screw size : M3x6, recommended tightening torque : 0.4 N·m [4 kgf·cm])
- (10) For an instrument with 24V power supply, supply power from a SELV circuit.




■ Terminal configuration

<REX-DP110>



- Power supply used
 - 100 to 240 V AC (50/60 Hz)
 - 24 V AC (50/60 Hz)
 - 24 V DC


<REX-DP410>



- Power consumptions
 - 9 VA or less (at 240 V AC)
 - 6 VA or less (at 100 V AC)
 - 6 VA or less (at 24 V AC)
 - 145 mA or less (at 24 V DC)

● Crimp-style terminal lug

Therefore, use the lug suitable for a screw of M3.



Recommended tighten torque: 0.4 N·m [4 kgf·cm]


Maximum allowance tighten torque: 1 N·m [10 kgf·cm]

NOTE


Terminals which are used according to the controller type are all removed.

4. PARTS DESCRIPTION

<REX-DP110>



<REX-DP410>



① Measured value (PV) display : Displays measured value (PV).


5. ERROR DISPLAYS

● Error display

	RAM failure (Incorrect set data write, etc.)	Please contact your nearest RKC sales office or agent.
--	--	--

● Overscale and Underscale

Measured value (PV) is flashing	PV is outside of input range.	<div style="border: 1px solid black; padding: 5px; text-align: center;"> ⚠ WARNING </div> <p>To prevent electric shock, always turn off the power before replacing the sensor.</p>
	Overscale PV is above the high input display range limit.	
	Underscale PV is below the low input display range limit.	



6. INPUT RANGE TABLE

TC

Input type (Character)	Range	Code
K (K)	0 to 1372 °C 0 to 2502 °F	K 07 A3
J (J)	0 to 1200 °C 0 to 2192 °F	J 06 A3
R ^{#1} (r)	0 to 1769 °C 0 to 3216 °F	R 02 A2
S ^{#1} (s)	0 to 1769 °C 0 to 3216 °F	S 02 A2
B ^{#1} (b)	0 to 1820 °C 0 to 3308 °F	B 02 A2
E (E)	0 to 1000 °C 0 to 1832 °F	E 02 A2
N (n)	0 to 1300 °C 0 to 2372 °F	N 02 A2
T (T)	-199.9 to +400.0 °C -199.9 to +752.0 °F	T 01 A1
W5Re/W26Re (W)	0 to 2320 °C 0 to 4208 °F	W 02 A4
PL II (P)	0 to 1390 °C 0 to 2534 °F	A 02 A2
U (U)	-199.9 to +600.0 °C -199.9 to +999.9 °F	U 01 A1
L (L)	0 to 900 °C 0 to 1652 °F	L 05 A3

#1 : Accuracy is not guaranteed between 0 to 399 °C (0 to 799 °F).

RTD

Input type (Character)	Range	Code
Pt100 (P ^T)	-199.9 to +649.0 °C -199.9 to +999.9 °F	D 01 A1
JPt100 (J ^P)	-199.9 to +649.0 °C	P 01